Ordering number:ENN3323

Monolithic Digital IC

LB1619M

3-Phase Brushless Motor Driver

Applications

The LB1619M is a 3-phase brushless motor driver IC ideally suited for use in VCR capstan motor driver, drum motor driver applications.

Features

- 120° voltage linear type.
- Speed control based on motor voltage control.
- Soft switching type eliminating noises caused by current switching and making the values of external capacitors smaller (comparable to those of chip capacitors).
- On-chip torque ripple compensation circuit.
- On-chip thermal shutdown circuit.

Package Dimensions

unit:mm

3073B-MFP30SD



Specifications

Absolute Maximum Ratings at Ta = 25˚C

Parameter	Symbol	Conditions	Ratings	Unit
Maximum supply voltage	V_{CC} max		16	V
Maximum supply voltage	V_S max		V_{CC}	V
Output current	I_O		1.5	A
Hall supply current	I_H		20	mA
Allowable power dissipation	Pd max		1.0	W
Operating temperature	Topr		–20 to +75	˚C
Storage temperature	Tstg		–55 to +125	˚C

Allowable Operating Ranges at Ta = 25˚C

Parameter	Symbol	Conditions	Ratings	Unit
Supply voltage	V_{CC}		6 to 16	V

(Design Notes) It should be noted that dielectric breakdown is liable to occur between pin 11 and other pins.

Electrical Characteristics at Ta = 25˚C, V_{CC}=12V, V_S=3V

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Supply current 1	I_{CC}	V_{BR}=5V		18	23	mA
Supply current 2	I_S	V_{BR}=5V		5.0	7.0	mA
Supply standby current	I_{CCOQ}	V_{STBY}=0V			180	µA
Output saturation voltage	$V_{O(sat)}$	I_{OUT}=1.0A, sink+source			2.3	V

Continued on next page.

Continued from preceding page.

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Output transistor breakdown voltage	$V_{O(sus)}$	I_{OUT}=20mA *	16			V
Output standby voltage	V_{OQ}	V_{BR}=5V	1.43	1.53	1.63	V
Hall amplifier input offset voltage	$V_{HOFFset}$	*	–5		+5	mV
Hall amplifier common-mode input voltage range	V_{HCOM}		1.4		2.8	V
Hall input-output voltage gain	G_{VHO}	Under specified circuit conditions	31.5	34.5	37.5	dB
Brake pin high-level voltage			2.0			V
Brake pin low-level voltage					0.8	V
Brake pin input current					100	µA
Brake pin leak current					–30	µA
FRC pin high-level voltage			2.8			V
FRC pin low-level voltage					1.2	V
FRC pin input current					100	µA
FRC pin leak current					–30	µA
Hall supply voltage	V_H	I_H=10mA $V_H^{(+)}$–$V_H^{(-)}$	0.8	1.0	1.5	V
Upper residual voltage	V_{XH}	I_{OUT}=100mA	0.40	0.6	0.75	V
Lower residual voltage	V_{XL}	I_{OUT}=100mA	0.5	0.6	0.7	V
Residual voltage inflection point				2.0		V
Overlap amount		V_{CC}=12V, V_S=3.5V	60	70	80	%
Operating temperature of thermal shutdown circuit		*	150	180	210	˚C
Hysteresis of thermal shutdoun circuit		*		15		˚C
Standby operating voltage					0.1	V
Standby bias current		Pin GND			10	µA
V_S OFF-state IC flow-out/in current		Number of revolutions : 1260rpm			0.8	A

Note) * : Values shown are design targets only. No measurements have been taken.
Overlap amount : Value measured at the time of shipment.

Pin Assignment



Note : All FRAME pins are connected to GND.

Truth Table

	Source sink	Input U	Input V	Input W	Forward/Reverse Control
1	W phase → V phase	H	H	L	L
	V phase → W phase				H
2	W phase → U phase	H	L	L	L
	U phase → W phase				H
3	V phase → W phase	L	L	H	L
	W phase → V phase				H
4	U phase → V phase	L	H	L	L
	V phase → U phase				H
5	V phase → U phase	H	L	H	L
	U phase → V phase				H
6	U phase → W phase	L	H	H	L
	W phase → U phase				H

Input :
- H : High level. One of the inputs should have a potential at least 0.2V higher than the other.
- L : Low level. One of the inputs should have a potential at least 0.2V lower than the other.

Forward/reverse control :
- H : 2.8 to 5V
- L : 0 to 1.2V



Equivalent Circuit Block Diagram



Pin Function

Unit (resistance : Ω)

Pin No.	Pin Symbol	Pin Voltage	Equivalent Circuit	Pin Description
1, 2 14, 15 16, 17 29, 30	FRAME (GND			GND for other than output.
3 5 7	U_{out} V_{out} W_{out}			Output pins.
4 6 8	U_R VR W_R			Output pins with resistor of 2Ω.
9	Rf			GND for output transistor.
10	V_S	<V_{CC}2		Power supply pin for fixing the output amplitude. Must be lower than V_{CC}2 voltage.
11	V_{CC}			Power supply pin for power amplifier circuit other than motor driver transistor.
13	ST, BY	L : 0.1V max H : 2.0V min		When this pin is grounded, all the circuitry stops operating. In this case, the supply current is approximately 100μA. In the normal operation mode, this pin is left open or made to be at a potential of more than 2V.
18	ANGLE			The hall input-output gain (slope of motor waveform) can be changed by changing the resistance connected across this pin and GND. ≈ 10kΩ.
19	BR	H : 2.0V min L : 0.8V max		Pin for stopping the motor L level : Motor drive (Less than 0.8V). H level : Motor stop (More than 2.0V).

Continued on next page.

Continued from preceding page. Unit (resistance : Ω)

Pin No.	Pin Symbol	Pin Voltage	Equivalent Circuit	Pin Description
20	FRC	H : 2.8V min L : 1.2V max		Pin for forward/reverse control of motor. L level : Forward (Less than 1.2V). H level : Reverse (More than 2.8V).
21 22	V_H^+ VH−			Pin for supplying the hall bias current. A voltage of approximately 1V is developed across (V_H^+) and (VH−).
23 24 25 26 27 28	$U_{IN}1$ $U_{IN}2$ $V_{IN}1$ $V_{IN}2$ $W_{IN}1$ $W_{IN}2$	1.4V min 2.8V max		U phase hall element input pin. Logic "H" : $U_{IN}1>U_{IN}2$ V phase hall element input pin. Logic "H" : $V_{IN}1>V_{IN}2$ W phase hall element input pin. Logic "H" : $W_{IN}1>W_{IN}2$

Note) Pin 12 (NC pin) must be left open.

Sample Application Circuit



Unit (resistance: Ω, capacitance: F)

Output Voltage Waveform



Upper overlap=$(2V\alpha-V_A-V_{XL}) / (V_A-V_{XL})\times100$[%]
Lower overlap=$(V_A+V_{XL}-2V\beta) / (V_A-V_{XL})\times100$[%]

1. Upper overlap
   DC voltage of upper amplitude : $V_S-V_{XH}=V_A$
   DC voltage of lower amplitude : V_{XL}
   Let the DC voltage at the intersection of two phases of the upper waveform be $V\alpha$:
   From the drawing shown above
   At upper overlap amount=$A/B\times100$[%]
   A $=V\alpha-1/2(V_S-V_{XH}+V_{XL})=V\alpha-1/2(V_A+V_{XL})$
   B $=(V_S-V_{XH})-1/2(V_S-V_{XH}+V_{XL})=1/2(V_A+V_{XL})$
   * Upper overlap
   $=(2V\alpha-V_A-V_{XL}) / (V_A-V_{XL})\times100$[%]

2. Lower overlap
   DC voltage of upper amplitude : $V_S-V_{XH}=V_A$
   DC voltage of lower amplitude : V_{XL}
   Let the DC voltage at the intersection of two phases of the upper waveform be $V\beta$:
   From the drawing shown above
   At lower overlap amount=$C/D\times100$[%]
   C $=1/2(V_S-V_{XH}+V_{XL})-V\beta=1/2(V_A+V_{XL})-V\beta$
   D $=1/2(V_S-V_{XH}+V_{XL})-V_{XL}=1/2(V_A-V_{XL})$
   * Lower overlap
   $=(V_A-V_{XL}-2V\beta) / (V_A-V_{XL})\times100$[%]